



Creating a Dial Profile in Survey Controller using the MiFi Device

To create a Dial Profile to connect to a VRS using the Verizon MiFi device perform the following steps.


1. From the Main Menu in Survey Controller tap on Configuration.



2. Tap on Dial profiles.



3. Tap on New at the bottom of the screen.



4. Enter the following information.

Name: Enter a name for your dial profile.


Profile type: Internet rover

Network connection: localhost


Bluetooth modem: None

Modem PIN: Leave Blank

APN: Tap on the right arrow and select None.



Tap on .



NTRIP Configuration

Use NTRIP: Use proxy server:

Connect directly to Mountpoint:

NTRIP username: NTRIP password:

IP Address: IP Port: 2/3

Esc Test Config Enter

Use NTRIP: Tap on the box to enter a check.


Use proxy server: Leave unchecked.

Connect directly to Mountpoint: Tap on the box to enter a check.

Mountpoint name: Enter the name of the mount point. If you do not know the name of the mountpoint then leave it blank and Survey Controller will fill it in for you automatically when you connect to the VRS for the first time.

NTRIP username: Enter the user name provided to you by your VRS provider. **Note: This file is case sensitive.**

NTRIP password: Enter the password provided to you by your VRS providers. **Note: This field is case sensitive.**



NTRIP Configuration

Use NTRIP: Use proxy server:

Connect directly to Mountpoint:

Mountpoint name: NTRIP username:

NTRIP password:

Esc Test Config Store


Tap on 2/3.

IP Address: Enter the IP address of the VRS Service. **Note: This information is provided to you by your VRS service provider.**

IP Port: enter the Port of the VRS Service. **Note: This information is provide to you by your VRS service provider.**


Connection type: GPRS

Send user identity info: Leave unchecked.



Tap on Store.

Note: If you get a message about the network connection does not exist tap OK to ignore it.



Name	Type
MiFi	Internet rover
NC VRS	Internet rover

- Now follow the steps in the VRS Rover with Survey Controller Getting Started Guide.